

# ROP-110/EU

## CONVENTIONAL MANUAL CALL POINT

The **ROP-110** call point is used to manually trigger an alarm when a fire is discovered. The call point is designed to work with the **CSP-104**, **CSP-108**, **CSP-204** and **CSP-208** fire alarm control panels.

- resettable plastic pane
- key to enable:
- testing
- resetting

LED to indicate activation of the call point

**ROP-FLAP** – optional protective cover to prevent unintentional activation

### TECHNICAL DATA

Operating temperature range	-10°C...+55°C
Weight	139 g
Maximum humidity	95%
Dimensions	87 x 87 x 47 mm
Current draw when detecting	0 mA
Current draw when emitting an alarm	25 mA
Power supply voltage	9...30 V DC

