

ROP-401/EU

ADDRESSABLE MANUAL CALL POINT FOR OUTDOOR USE

The **ROP-400** call point for outdoor applications is used to manually trigger an alarm when a fire is discovered. It is designed to operate in the detection line of the **ACSP-402**; addressable fire alarm control panel.

- resettable plastic pane
- **ROP-KEY-U** key (sold in set) to enable:
 - testing
 - resetting

LED indicator/li>

double-sided short-circuit isolator

power supply from the detection line

mounting box included

optional protective cover to prevent unintentional activation – **ROP-FLAP**

TECHNICAL DATA

| | |
|-------------------------------------|------------------|
| Operating temperature range | -25°C...+70°C |
| Weight | 180 g |
| Maximum humidity | 95% |
| Current draw when detecting | 170 µA |
| Current draw when emitting an alarm | 450 µA |
| IP rating | IP66 |
| Power supply voltage | 18...26 V DC |
| Dimensions without holders | 87 x 87 x 53 mm |
| Dimensions with holders | 117 x 87 x 53 mm |

